

ClickStart Configuration Template

ClickStart configures the router with the following configuration:

```
CD
SET SCREENLENGTH 20
SET COUNTRYGROUP 1
SET LAN MODE ANY
SET WAN MODE ONLY
SET AGE OFF
SET MULTIDESTINATION OFF
SET SWITCH 5ESS
SET 1 SPID 044100
SET 1 DIRECTORYNUMBER 0441
SET 2 SPID 044200
SET 2 DIRECTORYNUMBER 0442
SET 1 DELAY 30
SET 2 DELAY 30
SET BRIDGING ON
SET LEARN ON
SET PASSTHRU OFF
SET ENCAPSULATION CPP
SET SPEED AUTO
SET PLAN NORMAL
SET 1 AUTO ON
SET 2 AUTO ON
SET 1 NUMBER
SET 2 NUMBER
SET 1 RINGBACK
SET 2 RINGBACK
SET SYSTEMNAME cpa760
LOG CALLS TIME VERBOSE
SET UNICASTFILTER OFF
DEMAND 1 THRESHOLD 0
DEMAND 2 THRESHOLD 48
DEMAND 1 DURATION 1
DEMAND 2 DURATION 1
DEMAND 1 SOURCE LAN
DEMAND 2 SOURCE BOTH
TIMEOUT 1 THRESHOLD 0
TIMEOUT 2 THRESHOLD 48
TIMEOUT 1 DURATION 0
TIMEOUT 2 DURATION 0
TIMEOUT 1 SOURCE LAN
TIMEOUT 2 SOURCE BOTH
SET REMOTEACCESS PROTECTED
SET LOCALACCESS ON
SET LOGOUT 5
SET CALLERID OFF
SET PPP AUTHENTICATION IN CHAP
```

```
SET CALLBACKID OFF
SET CALLBACK OFF
SET PPP AUTHENTICATION OUT CHAP
SET PPP CALLBACK REQUEST OFF
SE PPP CALLBACK REPLY OFF
SET CPP NEGOTIATION INTEGRITY 10
SET CPP NEGOTIATION ABORT DISCONNECT
SET CPP NEGOTIATION COUNT 6
SET CPP NEGOTIATION RETRY 1000
SET PPP NEGOTIATION INTEGRITY 10
SET PPP NEGOTIATION COUNT 10
SET PPP NEGOTIATION RETRY 3000
SET PPP TERMREQ COUNT 2
SET PPP MULTILINK ON
SET COMPRESSION STAC
SET CPP PROTOCOL ORDERED
SET SNMP CONTACT
SET SNMP LOCATION
SET SNMP TRAP COLDSTART OFF
SET SNMP TRAP WARMSTART OFF
SET SNMP TRAP LINKDOWN OFF
SET SNMP TRAP LINKUP OFF
SET SNMP TRAP AUTHENTICATIONFAIL OFF
SET VOICEPRIORITY INCOMING INTERFACE PHONE1 CONDITIONAL
SET VOICEPRIORITY OUTGOING INTERFACE PHONE1 ALWAYS
SET CALLWAITING INTERFACE PHONE1 OFF
SET VOICEPRIORITY INCOMING INTERFACE PHONE2 CONDITIONAL
SET VOICEPRIORITY OUTGOING INTERFACE PHONE2 ALWAYS
SET CALLWAITING INTERFACE PHONE2 OFF
SET USER LAN
SET IP ROUTING ON
SET IP ADDRESS 192.168.99.219
SET IP NETMASK 255.255.255.0
SET IP RIP UPDATE PER
SET USER Internal
SET USER Standard
SET PROFILE POWERUP ACTIVATE
SET PROFILE DISCONNECT KEEP
SET USER ev-2060
SET PROFILE ID 000000000000
SET PROFILE POWERUP ACTIVATE
SET PROFILE DISCONNECT KEEP
SET ENCAPSULATION PPP
SET 1 NUMBER 0451
SET 2 NUMBER 0452
SET IP ADDRESS 0.0.0.0
SET IP FRAMING NONE
SET IP RIP UPDATE PER
SET IP ROUTING ON
```

<HR>

[Return to ClickStart Technical Details](#)

[Return to ClickStart Home Page](#)
