

ClickStart Configuration Template

ClickStart configures an ISDN router with the following configuration:

```

service timestamps debug
service timestamps log
!
hostname hostname
!
service password-encryption
enable-secret password password
line vty 0 5
password password
!
isdn switch-type switch-type
username remote-name password remote-password
!
interface ethernet 0
ip address ip-address ip-mask
ip helper-address dns-address
no lat enabled
no mop enabled
!
interface bri 0
ip unnumbered ethernet 0
encapsulation ppp
dialer map ip 192.168.254.254 name remote-name speed 56 remote-number
isdn spid1 spid1
isdn spid2 spid2
ppp authentication chap
dialer-group 1
!
ip classless
ip route 0.0.0.0 0.0.0.0 192.168.254.254
ip route 192.168.254.254 interface bri 0
logging buffered
access-list 101 deny udp any any eq snmp
access-list 101 deny udp any any eq ntp
access-list 101 permit ip any any
snmp-server community public R0
dialer-list 1 list 101
!
end

```

<HR>

[Return to ClickStart Technical Details](#)

[Return to ClickStart Home Page](#)